

# MT65 Beluga II

Portable Data Collector

#### 4.0" CAP Touch 1D 20 0 4G ... AMERA MICRO SD GPRS ~ 1.2 M DROP **IP65** MICRO 3700mAh LISB



### Features

#### Rugged construction.

The rugged housing of the Beluga II is sealed to IP65 standards for protection against dust and water and withstands 1.2m drops to concrete.

#### • Extended battery life.

The Beluga II provides up to 10 hours of battery life on the go.

#### • Superior barcode reading performance.

Armed with Newland's fifth-generation of UIMG technology, the Beluga II can decode even poor quality barcodes, such as soiled or wrinkled barcodes, with ease.

#### • Heavily customised Android.

The value-added features of the Beluga II, including application protection and admin tools, seek to shore up Android's data security.

## **Application Scenarios**

#### Diverse functionalities.

The MT65 Beluga II offers Bluetooth/Dual band Wi-Fi 2.4GHz and 5GHz/4G/3G/GPS/ Camera functionalities to meet various application needs.

#### Accessories.

For your convenience, MT65 Beluga II can be used with a pistol grip and a charging cradle.

#### • Current models released.

MT6550-1W (1D Laser) MT6550-3W (1D CCD) MT6550-4W (2D CMOS)



www.newland-id.com

Logistics, express delivery services, warehouse management, retail chains, food traceability, healthcare, distributor management, manufacturing, electricity meter reading, inventory counting.



# MT65 Beluga II

Portable Data Collector

Performance	Processor	1.3GHz quad-core 64-bit processor	
	Operating System	Android 5.1 (64-bit)	
	Memory	1GB RAM, 8GB ROM Micro USB 2.0, Battery charging over USB supported	
	Interface		
Physical	Dimensions	166(L) ×73(W) ×26(H) mm	
	Weight	330g (including battery)	
	Display	4"WVGA (800×480) capacitive touch screen	
	Keypad	30 keys (side keys included) with backlightVibrator, speaker and multi-color LEDs3.7V, 3700mAh10 hours	
	Notification		
_	Battery		
_	Expected Battery Life		
_	Expected Charge Time	4.5-5 hours (cha	arge via AC adapter)
	Camera	8 megapixels, auto focus, with LED flashlight	
_	GPS	GPS	
_	Expansion	Micro SD card (max. 32GB) slot	
	AC Adapter	Output: DC5V, 2.0A Input: AC100~240V, 50~60Hz	
Environmental	Operating Temperature	-20°C to 50°C (-4°F to 122°F )	
-	Storage Temperature	-30°C to 70°C (-22°F to 158°F)	
	Humidity	5% to 95% (non-condensing)	
_	Static Discharge	±15 kV (Air discharge), ±8 kV (Direct discharge)	
_	Drop	1.2m drops to concrete (for six sides, one drop per side)	
	Sealing	IP65	
Barcode	1D Barcode	CCD (≥4mil)	Code 128, UCC/EAN-128, AIM 128, EAN-8, JAN-8, EAN-13, ISBN/
Scanning		Laser (≥4mil)	ISSN, UPC-E, UPC-A, Interleaved 25, ITF-6, ITF-14, Deutsche 14,
			Deutsche 12, COOP 25, Matrix 25, Industrial 25, Standard 25,
			Code 39, Codabar/NW7, Code 93, Code 11, Plessey, MSI/
			Plessey, GS1 Databar.
	2D Barcode	CMOS (≥5mil) with Laser Aimer	All major 1D symbologies, PDF417, QR Code, Data Matrix, etc
RFID	13.56MHz RFID		ISO14443A/B, MIFARE, FeliCa, NFC Forum Tags, ISO15693
Wireless	WLAN RADIO		IEEE 802.11 a/b/g/n, 2.4GHz and 5GHz
	WWAN RADIO	2G	GSM/GPRS/EDGE: B2, B3, B5, B8 (850/900/1800/1900MHz)
		3G	WCDMA(B1, B2, B5, B8); CDMA2000 1X/ EV-DO Rev. A (BC0);
			TD-SCDMA(B34, B39)
		4G	TD-LTE (B38, B39, B40, B41)
_			FDD-LTE (B1, B3, B7, B20)
	WPAN RADIO		Bluetooth 4.0 LE
Optional	Charging cradle, battery, AC adapter, cable, wrist strap, shoulder strap, scanner pistol grip, batch battery		
Accessories	charger.		

Accessories Charger. Specifications are subject to change without notice.

For a complete listing of all supported bar code symbologies, please refer to the user guide.

Version: V2.0

Newland EMEA +31 (0) 345 87 00 33 info@newland-id.com

Newland France +31 (0) 345 87 00 33 france@newland-id.com **Newland D-A-CH** +49 (0) 294 298 76758 info@newland-id.de

Newland Middle East +31 (0) 345 87 00 33 middleeast@newland-id.com Newland UK +44 (0) 1442 212 020 sales@newland-id.co.uk

Newland South Africa +27 (0) 11 553 8010 info@newland-id.co.za Newland Nordic & Baltic +46 (0) 708 847 767 nordic@newland-id.com

**Newland Italy** +39 (0) 342 056 2227 italy@newland-id.com Newland Ibérica +34 (0) 93 303 74 66 info@newland-id.es

Newland Russia +31 (0) 345 87 00 33 russia@newland-id.com